

Bitronics® PowerPlex II

The PowerPlex II (PPX II) is a new Automation Transducer built in the same package as the original PowerPlex, or with digital I/O added, in the M571 case. It is an Ethernet transducer with fast, 1-cycle updates that can be used in SCADA automation schemes and in synchronizing applications in conjunction with PLCs. It is an excellent choice as a replacement for the Bitronics M571 in non-recording applications. Two sets of three-phase voltages that allow direct connect for 600V ac systems are provided.

The PowerPlex II transducers are simple to set up and use, and provide the following features:

Communications

- No need for PC software – Ethernet service port provides access to web server in the instrument so meters can be interfaced with just a web browser for viewing and configuration
- Ethernet protocol support for DNP3, Modbus TCP, EtherNet/IP (with or without Device Level Ring (DLR) redundancy) or IEC 61850
- Built-in Ethernet switch allows pass-through from one device to another
- An option for both standard secondary “optimal resolution” or primary units makes communications with SCADA/RTU more flexible
- Optional display port and IRIG-B port
- Optional configurable RS-232/RS-485 serial port supports Modbus or DNP3 serial protocols

Measurements

- Full basic measurement & recording set with demand and harmonic values plus phase angle, voltage differential and slip frequency used in synchronizing applications
- 0.2% revenue accuracy
- .001Hz accuracy
- Updates every 1 cycle
- Optional trend recording

Built for the Substation

- Wide-range universal power supply
- Rugged aluminum case
- Reduce inventory cost as one model covers all wiring options
- Easy to mount with compact transducer footprint

Applications

- Synchronizing, voltage control, power factor control, and load shedding
- Digital front-end to SCADA systems
- Intelligent Electronic Device (IED) interfacing to RTUs and PLCs
- Plant equipment, line, power & energy monitoring
- Breaker status, rack-in, rack-out in switchgear
- Trend: transformer loads and voltages in E/M relay substations, battery voltage, Total Harmonic Distortion

Environmental

- Operating temperature range -40° to 70°C, storage temperature -40° to 85°C
- Humidity 0-95% non-condensing
- Surge withstand to ANSI/IEEE C37.90.1: 2002
- UL/CSA Recognized, File Number E164178, CE Marked



Specifications

Dimensions:

Standard chassis: 5.28" H x 5.60" W x 5.63" D – overall depth including handle is 5.75" D (134mm H x 142mm W x 143mm D – overall depth including handle is 146mm D)
Wide chassis (with I/O and serial port): 5.2" H x 8.5" W x 5.9" D (132mm H x 216mm W x 150mm D)

Weight:

Standard chassis: 2.3 lbs. (1.04 kg)
Wide chassis (with I/O and serial port): 3.5 lbs. (1.59 kg)

Power Supply: 12 – 40V dc nominal, intended to connect to 12 and 24V batteries or 48-250V dc/55-240V ac with built in monitoring

Current Inputs: 1A nominal to maximum of 2A or 5A nominal to maximum of 10A (2x overload)

Voltage Inputs: 600V ac nominal, 45-65Hz

Outputs: Dual RJ45 10BaseT/100BaseTX ports (Ethernet switch) for service port functions, Modbus or DNP3 TCP/IP support; IEC 61850 support optional display and IRIG-B ports

Digital Inputs: Optional 4 or 8; High speed, suitable for 1ms SOE

- Nominal Input Range: 24V dc to 250V dc
- Threshold Voltage: 15V dc +/-1V or 80V dc +/-5V (at 25C)
- Input Resistance: 33kohm
- Input De-bounce Time: Selectable, from 1 ms to 2 s

Digital Outputs: Optional 4

- Tripping duty relay
- Resistive: 30A
- Continuous Carry: 5A
- Break Inductive @48V dc: 700mA
- Break Inductive @125V dc: 200mA
- Output Operate Time (time from command by Host, does not include protocol delays):
 - Assert (Close time with “N.O.” jumper): 8ms
 - Release (Open time with “N.O.” jumper): 3ms

Isolation: I/O Terminals to Case: 2000Vac, 1 min. I/O Terminals to Channel: 2000Vac, 1 min (channel 4 to other channels)



IP Address Identity Tool

The PPX II supports the Inverse Address Recognition Protocol (InARP), a software utility program that requests the IP address for a specific MAC address on an Ethernet network and can also scan for a range of MAC addresses and print the IP address for any devices which respond.

| Available Measurements | |
|--|--------|
| Available Measurements | PPX II |
| Amps A, B, C, Residual | x |
| Average 3-Phase Amps | x |
| Average 3-Phase Volts (1 & 2) | x |
| Average Volts, Avg. Max Volts, Avg. Min Volts AN, BN, CN, AB, BC, CA (Bus 1) | x |
| Avg. Watts, Avg. Max Watts, Avg. Min Watts A, B, C, Total | x |
| Average VARs, Avg. Max VARs, Avg. Min VARs A, B, C, Total | x |
| Average VAs, Avg. Max VAs, Avg. Min VAs A, B, C, Total | x |
| Class 0 Response Setup | x |
| CT Scale Factor/Scale Factor Divisor | x |
| Demand Amps, Max Amps A, B, C, Residual | x |
| Demand Fundamental Amps, Max Fund. Amps A, B, C, Residual | x |
| Displacement Power Factor A, B, C, Total | x |
| Factory Version Hardware/Software | x |
| Frequency (System) | x |
| Frequency Volts A, B, C (1 & 2) | x |
| Fund. Amps A, B, C, Residual | x |
| Fund. Volts AN, BN, CN, AB, BC, CA (1 & 2) | x |
| Health | x |
| Heartbeat | x |
| K-factor Amps A, B, C, Residual | x |
| Meter Type | x |
| Phase Angle Amps A, B, C | x |
| Phase Angle Volts A, B, C; AB, BC, CA | x |
| Phase Angle Volts A 1-2, B 1-2, C 1-2 | x |
| Power Factor A, B, C, Total | x |
| Protocol Version | x |
| PT Scale Factor/Scale Factor Divisor | x |
| Slip Frequency Volts A 1-2, B 1-2, C 1-2 | x |
| Symmetrical Components Bus 1 & 2 Volts (Magnitude and Angle) | x |
| Symmetrical Components Current (Magnitude and Angle) | x |
| Tag Register | x |
| TDD Amps A, B, C, Residual | x |
| TDD Denominator A, B, C | x |
| THD Volts AN, BN, CN, AB, BC, CA | x |
| Unbalance Amps | x |
| Unbalance Volts (1 & 2) | x |
| Uncompensated VARs, Total | x |
| Uncompensated Watts, Total | x |

| Available Measurements | |
|--|---|
| VA-Hrs | x |
| VAR-Hrs Lag/Lead | x |
| VARs A, B, C, Total | x |
| VAs A, B, C, Total | x |
| Volts AN, BN, CN, AB, BC, CA (1 and 2) | x |
| Volts Aux1-Aux2 | x |
| Watt-Hrs Net/Normal/Reverse | x |
| Watts A, B, C, Total | x |

Web-based set up of Trend Recorder



The PowerPlex II Tethered Display (PPXIITD) provides local or detached indication of measured values

PowerPlex II with added I/O and serial port in M571 case



Copyright © 2021 NovaTech, LLC. All rights reserved. All brand and product names mentioned in this document are trademarks of their respective owners. NovaTech and Bitronics are registered trademarks of NovaTech, LLC. The information in this literature is subject to change without notice and is not to be construed as a warranty. PowerPlexII Datasheet_100821